

## GV60 Bidirectional Control System

### POWER CONSUMPTION GUIDE

FOR OEM USE ONLY

**NOTICE**

Content not for use by general public or for online publishing. For OEM use only.

Product/Component	Power Consumption				Radiated Power Output
	Standby	Nominal	Motor turn	Ignition	
<b>Receiver</b> (B6R-R8(A)...)	CSA + CE: 0.7 mW	CSA + CE: 0.8 mW	CSA + CE: 0.25 W	CSA + CE: 3.0 W	CSA: 90.8 $\mu$ V/m CE: -3.5 dBm
<b>Receiver</b> (G6R...)	CSA + CE: 0.7 mW	CSA + CE: 0.8 mW	CSA + CE: 0.25 W	CSA + CE: 3.0 W	—
<b>V Module</b> (G6R-B...)	CSA + CE: G6R-B...V2: 0.5 W G6R-B...V3: 0.3 W	Depends on connected devices (fan, light)	—	—	—
<b>myfire Wi-Fi Box</b> (B6R-W2...)	max. 0.03 W	max. 0.5 W	—	—	19.8 dBm
<b>Symax Handset</b> (battery only)	—	—	—	—	CSA: 90.8 $\mu$ V/m CE: -3.5 dBm
<b>myfire Puck Handset</b> (battery only)	—	—	—	—	CSA: 84.5 $\mu$ V/m CE: -18.5 dBm
<b>G6R Handset</b> (Standard, battery only)	—	—	—	—	CSA: 74.9 $\mu$ V/m CE: -7.2 dBm
<b>G6R Handset</b> (Display/Timer/Thermostat) (battery only)	—	—	—	—	CSA: 72.8 $\mu$ V/m CE: -7.2 dBm